



PANACEA TURN SIGNAL INSERTS

5428

PARTS INCLUDED

- 2 3-1/4" Panacea Turn Signal Inserts — Red Lens
- 1 Dielectric Grease
- 1 Installation Instructions

Please read and understand entire instructions before starting installation.

THANK YOU FOR CHOOSING KÜRYAKYN!

IN ORDER TO PROTECT YOU AND OTHERS FROM POSSIBLE INJURY AND/OR PROPERTY DAMAGE OR LOSS, PLEASE PAY CLOSE ATTENTION TO ALL INSTRUCTIONS, WARNINGS, CAUTIONS AND ATTENTION NOTES REGARDING THE USE AND CARE OF THIS PRODUCT.

CAUTION! This indication alerts you to the fact that ignoring the contents described herein can result in potential injury or material damage.

ATTENTION! This indication alerts you to the fact that ignoring the contents described herein may negatively affect product performance and functionality.

TOOLS SUGGESTED

Phillips screwdriver, Test Light

STRICTLY OBSERVE THE FOLLOWING GUIDELINES IN ORDER TO USE THE PRODUCT PROPERLY AND AVOID POTENTIALLY DANGEROUS ACCIDENTS.

ATTENTION!

This Panacea product complies with FMVSS #108 when the controller supplied with the Panacea Taillight is operated in "DOT Mode". When in "DOT Mode", the Panacea Taillight and both Panacea Turn Signals will illuminate red as running lights, bright red as brake lights, and the appropriate Panacea Turn Signal will flash amber when a turn signal is activated. FMVSS #108 makes no provision for flashing brake or amber indicators within the taillight, so those features are disabled when "DOT Mode" is selected on the controller. Selecting "Panacea Mode" on the controller enables the flashing brake light feature and the amber chevron within the taillight when a turn signal is activated. Operation in Panacea Mode is at the discretion of the customer and Kuryakyn assumes no liability for situations created from operating these lights in Panacea Mode.

STEP 1

Read and understand all steps in the instructions before starting the installation. Park the motorcycle on a hard, level surface and turn off the ignition.

-cont.-

5428-21HD-0211

CUSTOMER SERVICE

877.370.3604 (toll free)

INSTALLATION QUESTIONS

techsupport@kuryakyn.com
or call 715.247.2983

LIMITED WARRANTY

Kuryakyn warrants that any Kuryakyn products sold hereunder, shall be free of defects in materials and workmanship for a period of one (1) year from the date of purchase by the consumer excepting the following provisions:

- Kuryakyn shall have no obligation in the event the customer is unable to provide a receipt showing the date the customer purchased the product(s).
 - The product must be properly installed, maintained and operated under normal conditions.
 - Kuryakyn makes no warranty, expressed or implied, with respect to any gold plated products.
 - Kuryakyn shall not be liable for any consequential and incidental damages, including labor and paint, resulting from failure of a Kuryakyn product, failure to deliver, delay in delivery, delivery in nonconforming condition, or for any breach of contract or duty between Kuryakyn and a customer.
- Kuryakyn products are often intended for use in specific applications. Kuryakyn makes no warranty if a Kuryakyn product is used in applications other than intended.
- Kuryakyn electrical products are warranted for one (1) year from the date of purchase by the consumer. L.E.D.'S contained in components of Kuryakyn products will be warranted for defects in materials and workmanship for 3 years from the date of purchase where as all other components shall be warranted for one(1) year. This includes, but is not limited to; control modules, wiring, chrome & other components.
- Kuryakyn makes no warranty of any kind in regard to other manufacturer's products distributed by Kuryakyn. Kuryakyn will pass on all warranties made by the manufacturer and where possible, will expedite the claim on behalf of the customer, but ultimately, responsibility for disposition of the warranty claim lies with the manufacturer.

ABOUT OUR CATALOG

For purchasing Kuryakyn® products, you can receive a complete catalog free of charge.

Send the Proof-of-Purchase below with your address to: Kuryakyn, P.O. Box 339, Somerset, WI 54025.

Please indicate either Accessories Catalog for Harley-Davidson® or GL & Metric Cruisers.

Be sure to ask your local dealer about other Kuryakyn® products, the motorcycle parts and accessories designed for riders by riders.

©2005 Kuryakyn USA® All Rights reserved.

kuryakyn.com



STEP 2 Remove the lenses from the stock turn signal fixtures. The screws will be re-used.

STEP 3 Remove the stock turn signal bulb from the fixtures by pushing the bulb slightly inward and turning counter clockwise.

CAUTION! LED circuit boards are polarity sensitive! Use a test light to check the polarity of the bike's wiring before connecting the LED circuit board. Küryakyn is not responsible for damage to the LED circuit board caused by reversed polarity.

CAUTION! Use a test light to verify wire functions before connecting the LED circuit board to non-stock wiring. Küryakyn is not responsible for damage to the LED circuit board caused by non-stock wiring

ATTENTION! Küryakyn recommends the use of dielectric grease on electrical connections.

STEP 4 Install the Panacea light connector in the same manner the stock bulb was removed. Using a screwdriver in the slot on the connector may ease installation. PIC 1

STEP 5 Attach the Panacea Lenses to the light fixtures using the stock screws. Tighten the screws to snug — do not over tighten. PIC 2

